SWMS No 004 SJD Electrical Job Safety Analysis / Safe Work Method Statement										Page 1 of 7				
	SJD ELECTRICAL PTY L	.TD - ABN 53	127 802 608 - ACN	127 802 608 - E	LECTRICAL LICENC	E 68608 - QBCC L	ICENCE 1270514 - A	RC LICENCE AU1980	1 - MOLEX L	LICENCE CIAU33	372			
Safe	Work Method Sta	tement Titl	e: SWMS: 004	CABLE AND	LADDER TRA	Y INSTALLATI	ION			Date Created 00/00/16	:			
Project Name: Person responsible for ensuring compliance with this SWMS:									Review Date: 00/00/17					
Proje	ect/Client:				Job No:		Authorised E	Ву:		Revision No.	0			
			Licences, Peri	nits, Compet	tencies Require	ed: (tick items i	relevant to this ta	sk and site)						
□ Cor	nfined Space		Work at Heights		□ Excavation		□ Hot Work		□ Radia	tion				
	ite Card		EWP		□ Electrical Lic	ense	□ Rescue and	Resuscitation	□ Netwo	ork Access				
			Comm	on Hazards t	o Manage: (tick	items relevant	to this task and s	site)						
□ Mai	nual handling		Working at Heigl	nts	□ Risk of Elect	ric Shock	□ Slips, Trips	and Falls	□ House	Housekeeping				
POSSI	RD CLASSIFICATION BLE RESULTS Consequence x Likeli		RARE A	UNLIKELY B	Probability POSSIBLE C	LIKELY D	ALMOST CERTAIN E		Elimination Substitution					
Ø	Catastrophic	5	Medium (M)	High (H)	High (H)	Extreme (E)	Extreme (E)		Isolation	1				
nce	Major	4	Medium (M)	Medium (M)	High (H)	High (H)	Extreme (E)	\	Engineerii	ng /				
Consequences	Moderate	3	Low (L)	Medium (M)	High (H)	High (H)	High (H)		Admin					
nse	Minor	2	Low (L)	Low (L)	Medium (M)	Medium (M)	High (H)		Aumin	PPE IS THE 'LAST LINE OF DEFENCE"				
တ	Insignificant	1	Low (L)	Low (L)	Low (L)	Medium (M)	Medium (M)		PPE					
	RISK RATING							onably Practicab						
H = Hi M = M	igh risk Only acceptable ledium risk Undesirable ow risk Tolerable		Implement strict Reasonably Pra Specify, docume	control measures acticable (ALARF ent and implement continue without	to reduce risk to an and preferably Me	acceptable level. A dium rating. Opera s and additional ma	Activity must not continutions Manager and/orunagement actions to	risk mitigation measur nue until the level of ri Project Supervisor ap reduce the risk to ALA	sk is reduced oproval of the	to As Low As risk controls is r	equired.			
Ba: PPE be u	E to ISEC HEARING AND EYE PROTECTION MUST BE WORN	SAFETY GOGGLES MUST BE WORN	FACE SHIELD MUST BE WORN	SAFETY VEST MUST BE WORN	NARD HAT RES	FACE MASK PREATHING AP MUST BE W	PARATUS DUST MASK MUST BE WORN		DOT PROTECTION MUST BE WORN	FALL ARREST EQUIPMENT MUST BE USED	PROTECTIVE CLOTI MUST BE WORN			
	Other PPE:													

Safe Work Method Statement Title: SWMS: 004 CABLE AND LADDER TRAY INSTALLATION

Job Task #	Job Step	Potential Health, Safety and Environmental Hazards	PROBABILITY	CONSEQUENCE	RATING	Control Measures	PROBABILITY	CONSEQUENCE	RATING	PERSON(S) RESPONSIBLE
1	Planning and preparation	Non-compliance with current legislative requirements and company processes.	D	4	Н	All personnel to complete site specific induction. All personnel to have completed company specific induction. Personnel are to hold the required licenses and certificates for the work, and be assessed as competent to use or operate equipment and plant. All personnel must read, understand and sign off on this SWMS. All personnel are given the opportunity to provide input into the content of this SWMS. Daily pre-starts will be held at the beginning of each shift. Any changes throughout the shift will be communicated prior to the commencement of the next task. A JSA is to be completed for any changes to the task. Ensure permit requirements are understood. A Risk Assessment has been carried out.	В	4	М	Work crew Supervisor Permit Holder
		Working outdoors with exposure to; - UV / high temperatures causing heat stress / dehydration / sunburn - Fauna and insects causing bites and stings	D	3	Н	'Check ins' during extreme weather conditions. Comply with the Queensland Worksafe heat stress procedure. Ensure there is an area in the shade for rest (preferably Crib Facilities). Work Breaks are compulsory at nominated times (preferably during the hotter parts of the day) Drink adequate water amount of water. Use sun block for protection from sun. Use insect repellent (if applicable). Keep an eye out for fellow workers showing signs of fatigue, and report it to your supervisor. If you are feeling fatigued- talk to your supervisor.	В	3	М	Work crew

Job Task #	Job Step	Potential Health, Safety and Environmental Hazards	PROBABILITY	CONSEQUENCE	RATING	Control Measures	PROBABILITY	CONSEQUENCE	RATING	PERSON(S) RESPONSIBLE
		Interactions with other trades working in the vicinity; - Inadvertently cause hazardous situation including trips, slips, falls	D	ъ	H Ensure other workers are informed and aware of all other trades working in the area Communicate potential interactions during prestart Install barricading and signage to delineate work area if required		В	3	М	Supervisor Work Crew
		Unauthorized access to work area by other authorized personnel without correct PPE. Poor ground conditions	onnel D		н	Follow all site rules and procedures. Wear all mandatory PPE and task specific PPE. If a hazard is identified in the work area – fix it immediately or if unable to do so, isolate the hazard and inform your supervisor immediately. Site wide barricading to be installed to restrict access to unauthorized personnel. Signage to be visible around all site and at all access points. All visitors must report to site office before entering site. All visitors to be escorted by a site inducted personnel member. Inspect path of travel for any obstructions and remove them.	В	3	M	Supervisor Work crew
		Uneven, loose, wet or soft ground at the work site.	С	2	,	Daily site inspections prior to commencement of work activities and at the conclusion of each work day. Regular housekeeping inspections including regular walk rounds to be conducted to ensure a clean and tidy work area.		2	101	Work crew
2	Work area preparation	Personal injury - - Cuts, strains, abrasions, burns - Possible eye injury - Dust inhalation (depends on surrounds – these tasks should not cause dust or fumes)	С	3	Н	Authority and empowerment to Stop the Job . Follow all site rules and procedures. Ensure correct manual handling techniques are followed. Wear all mandatory PPE and task specific PPE. Communicate task clearly with all work crew members. Ensure a thorough understanding of expectations. If a hazard is identified in the work area – fix it immediately or if unable to do so, isolate the hazard and inform you supervisor. Work on flat surface where practicable Secure all tools and/or equipment by lanyard or store in a toolbox/basket when on the work platform.	В	3	М	Work crew Supervisor

Job Task #	Job Step	Potential Health, Safety and Environmental Hazards	PROBABILITY	CONSEQUENCE	RATING	Control Measures		CONSEQUENCE	RATING	PERSON(S) RESPONSIBLE
3	Check layout and mark out	Personal injury – - Potential slips, trips and falls - Exposure to existing nails	С	3	Н	Ensure direct work area is clear and free from any potential trip hazards All tools are to be stored appropriately for easy access and to avoid becoming a trip hazard Work area to be check to ensure all exposed nails are removed Dispose of all loose items and rubbish appropriately	В	3	М	Work crew Supervisor
4	Secure fixings and supports using correct type and size bolts and fixings	Personal injury — - Struck by moving objects - Cuts, strains, abrasions, burns - Possible eye injury - Dust inhalation (depends on surrounds – these tasks should not cause dust or fumes) - Fall from heights (remove if not applicable)	С	4	н	Authority and empowerment to Stop the Job. Ensure correct manual handling techniques are followed. Wear all mandatory PPE and task specific PPE. If dust is present, a dust musk must be used. A dust extraction device will be used in the event dust becomes excessive. Refer to Working at Heights SWMS (remove if not applicable)	В	4	М	Work crew
5	Cut cable ladders or trays to fit using drop saw / angle grinder	Personal injury – - Struck by moving objects - Cuts, strains, abrasions, burns - Possible eye injury - Damage caused by noise - Dust inhalation (depends on surrounds – these tasks should not cause dust or fumes) - Fall from heights (remove if not applicable)	С	4	н	Authority and empowerment to Stop the Job. Ensure correct manual handling techniques are followed. Wear all mandatory PPE and task specific PPE. If dust is present, a dust musk must be used. A dust extraction device will be used in the event dust becomes excessive. Refer to Working at Heights SWMS (remove if not applicable)		4	М	Work crew
		Lack of experience in using drop saw / angle grinder Faulty / damaged equipment	D	4	Н	Conduct verification of competency on drop saw / angle grinder Visual inspection to be carried out on drop saw / angle grinder Ensure tools have been tested and tagged		4	М	Supervisor Work crew

Job Task #	Job Step	Potential Health, Safety and Environmental Hazards	PROBABILITY	CONSEQUENCE	RATING	Control Measures	PROBABILITY	CONSEQUENCE	RATING	PERSON(S) RESPONSIBLE
6	Secure ladders or trays to support	Personal injury – - Struck by moving objects - Cuts, strains, abrasions, burns - Possible eye injury - Dust inhalation (depends on surrounds – these tasks should not cause dust or fumes) - Fall from heights (remove if not applicable)	С	4	Н	Authority and empowerment to Stop the Job. Ensure correct manual handling techniques are followed. Wear all mandatory PPE and task specific PPE. If dust is present, a dust musk must be used. A dust extraction device will be used in the event dust becomes excessive. Refer to Working at Heights SWMS (remove if not applicable)	В	4	М	Work crew
7	Remove sharp edges and protruding fixings	Personal injury — C 4 H Authority and empowerment to Stop the Job. - Struck by moving objects - Cuts, strains, abrasions, burns - Possible eye injury - Damage caused by noise - Dust inhalation (depends on surrounds – these tasks should not cause dust or fumes) - Fall from heights (remove if not applicable) - Authority and empowerment to Stop the Job. Ensure correct manual handling techniques are followed. Wear all mandatory PPE and task specific PPE. If dust is present, a dust musk must be used. A dust extraction device will be used in the event dust becomes excessive. Refer to Working at Heights SWMS (remove if not applicable)		В	4	М	Work crew			
		Lack of experience in using drop saw / angle grinder Faulty / damaged equipment	D	4	Н	Conduct verification of competency on drop saw / angle grinder Visual inspection to be carried out on drop saw / angle grinder Ensure tools have been tested and tagged	В	4	М	Supervisor Work crew
8	Completion of task	Slips, trips, and falls	С	4	Н	Leave work area tidy. Store equipment in authorised access area (e.g. locked storage facility) Report any damage/defect to supervision and tag out any faulty equipment.		4	М	Work crew

Safe Work Method Statement Title: SWMS: 004 CABLE AND LADDER TRAY INSTALLATION

Personnel Qualifications and	Personnel Duties a	Training Paguired to Complete Work					
Experience Required	Supervisor	All Personnel	Training Required to Complete Work				
Personnel will need to be trained and confident.	Empower all personnel to STOP the JOB if required to do so.	All personnel to maintain tidy work area on site at all times. Personal Protective Equipment (PPE) to be worn at all times on site.	Supervisor to be trained in risk identification, assessment and control e.g. Job Safety Analysis (JSA).				
Appropriate industry and site specific induction.	Supervisor to carry out daily inspections of work site for hazards.	Ensure housekeeping is maintained throughout the task to avoid the risk of injury.	Electrician to be trained in hazard identification, Risk Level and control.				
Verification of competency to use drop saw / angle grinder.	Ensure appropriate permits are in place for the task (if applicable).	Barricading to be used as appropriate to protect others from working below elevated work.	Training in the use of specific tools. Inspection and maintenance of equipment to be conducted (where applicable) for the type of equipment / plant to be used.				

Engineering Details / Certificates / Australian Standards	Referenced – Codes of Practice / Regulations / Legislation
AS/NZS 3000 Wiring Rules	Work Health and Safety Act and Regulations 2011
 AS/NZS 3012:2010 Electrical Installations – Construction and Demolition 	Electrical Safety Act 2002 and Electrical Safety Regulations 2013
 Sites. AS/NZS 3017 - Electrical installations - verification guidelines AS/NZS 4826 - Safe working on or near low voltage electrical 	 Electrical Safety Code of Practice 2013 - Managing Electrical Risks in the Workplace Hazardous Manual Tasks Code of Practice 2011
installations and equipment	Managing risks of Plant in the workplace Code of Practice 2013.
	(remove any of the above that are not applicable for the task being undertaken)
Plant / Equipment Required (Mobile or Static)	Maintenance Checks / Calibration Intervals
 Portable hand tools, electrical power tools / drills (insulated tools) May require scissor lift, boom lift or cherry picker (refer to Scissor Lift / Boom Lift / Cherry Picker SWMS) May require compliance with Working at Heights SWMS Appropriate testing equipment 	 Hand tools and ladders to be checked daily. All electrical equipment to be tested and tagged. All equipment and tools to be used as per manufacturer's instructions. Elevated Work Platform/s in accordance with manufacturer's recommendations (remove if not applicable)

SJD Electrical Job Safety Analysis / Safe Work Method Statement

Page 7 of 7

Safe Work Method Statement Title: SWMS: 004 CABLE AND LADDER TRAY INSTALLATION

This SWMS has been developed in consultation and cooperation with employee / workers and relevant employer / persons conducting business or undertaking PCBU. I have read the above SWMS and I understand its contents. I confirm that I have the skills and training, including relevant certification to conduct the task as described. I agree to comply with safety requirements within this SWMS including risk control measures, safe work instructions and Personal Protective Equipment.

OVERALL RISK RATING AFTER CONTROLS	□ 1 LOW	□ 2 MODERATE	□ 3 HIG	Н	□ 4 ACUTE
EMPLOYEE / WORKER NAME	JOB ROLE / POSITION	SIGNATURE	DATE	TIME	EMPLOYER / PCBU / SUPERVISOR